

## MR-PD02-X

### 2 Way Splitter

Can be used to split a signal from a source or combine signals from multiple sources.

Additional Features:

- Bi-directional splitter/combiner.
- Wide frequency range.
- Reliable and stable performance.
- Small size allowing for easy installation.



### Specifications

#### **Electrical**

Frequency range	800-2500 MHz
Insertion Loss, Over 3 dB, typ. / max.	0.7 dB / 1.5 dB
Output VSWR, max.	2 : 1
Amplitude Balance, max.	0.4 dB
Phase Balance, max.	4°
Isolation, typ.	20 dB
Impedance	50 Ohm
Operating Power	33 dBm

#### **Mechanical**

Dimensions (L x W x H)	120 x 95 x 30 mm (4.7" x 3.7" x 1.2")
Weight	Less than 200 gr.
Number of Outputs	2
Connectors	N-Type, Female
Mounting	Planar / Wall / Ceiling Mount

#### **Environmental**

Operating Temperature Range	-10°C to +55°C
Humidity, min.	95%
Splash, Dust	Protected

Mars Antennas & RF Systems proprietary information

MARS reserves the right to make technical changes or modifications to any of its products and specifications without prior notice and without implementing such changes to prior supplied products. Product images are representative and indicative only. Warranty terms and general conditions of sale are applicable on any purchase of any product, available on MARS website.

3 Hamanor st. Holon 58861, P.O.Box 5 AZOR 58008, Israel

Tel: +972-3-5599661 • Fax: +972-3-5599677 • e-mail: mars@marsant.co.il • web: www.mars-antennas.com