



MA-WA35-12

3.5 GHz Subscriber Antenna

MARS Small Size Antenna covering the licensed band of 3.5 GHz is designed for LTE, WiFi, WLL and WiMAX applications.

Additional Features:

- High gain/size ratio.
- Small and unobtrusive profile.
- Suitable for both indoor and outdoor applications.



Specifications

Electrical Programme Control of the				
Frequency range	3.3-3.8 GHz			
GAIN, typ.	12 dBi			
VSWR, max.	1.5 : 1			
Polarization	Linear, Vertical or Horizontal (See Ordering Options)			
3 dB Beam-Width, H-Plane, typ.	35°			
3 dB Beam-Width, E-Plane, typ.	30°			
Side Lobes, min.	-11 dB			
Cross Polarization, min.	-15 dB			
Front to Back Ratio, min.	-20 dB			
Input power, max.	10 Watt			
Input Impedance	50 Ohm			
Lightning Protection	DC Grounded			
Mechanical				
Dimensions (HxWxD)	155 x 155 x 28 mm (6.1" x 6.1" x 1.1")			
Weight	250 gr.			
Connector	SMA, Female (At the Bottom of the Antenna)			
Back Plane	Aluminum; protected through chemical passivation			

Difficition (FIXVVD)	1 100 X 100 X 20 11111 (0.1 X 0.1 X 1.1)		
Weight	250 gr.		
Connector	SMA, Female (At the Bottom of the Antenna)		
Back Plane	Aluminum; protected through chemical passivation		
Radome	UV Protected Polycarbonate		
Mount	See Ordering Options		
Environmental			
Operating Temperature Bongs	400C to 1000C		

Operating Temperature Range	-40°C to +65°C			
Vibration	According to IEC 60721-3-4			
Flammability	UL94			
Water Proofing	IP-67			
Humidity	ETS 300 019-1-4, EN 302 085 (annex A.1.1)			
Chandand Campliana				

3	Laii	uaiu	CUI	пр	Hanc	<u>.e</u>
TSI	ΕN	302	085	V1	.2.3 –	- TS1

E.

Ordering Options	
MA-WA35-12	Antenna with SMA Female Connector suited for MNT-4L, MNT-4U or MNT-4G
MA-WA35-12B	Antenna with SMA Female Connector and mount
MA-WA35-12N	Antenna with SMA, Female Connector Suited for MNT-23 (optional wall/pole
	adjustable mount)
MA-WA35-12NB	Antenna with SMA, Female Connector and mount MNT-23
MA-WA35-12N & MNT-23H	Antenna with SMA Female Connector and MNT-23H for horizontal polarization

Patterns are available on our website

MARS Antennas & RF Systems proprietary information

MARS reserves the right to make technical changes or modifications to any of its products and specifications without prior notice and without implementing such changes to prior supplied products. Product images are representative and indicative only. Warranty terms and general conditions of sale are applicable on any purchase of any product, available on MARS website.